# 3765Z0

Right Angle Light




Peli leads the way yet again with the new 3765Z0 rechargeable right angle torch. Featuring downcast LEDs for illuminating your path, the 3765Z0 LED torch also features 194 lumens (high) and 92 lumens (low), and a flashing mode. Another first is a built in battery life indicator so you will know your battery level before you go in. Compact, rugged, and lightweight, the 3765Z0 LED light contains the latest technology, Peli's legendary build quality and lifetime guarantee of excellence (where applicable by law). Certified to ATEX Zone 0 (Category 1).

- 4 mode battery level indicating button
- Locking wheel securely holds 4 AA batteries
- Secure clip for hands-free use
- Tethered battery door allows for quick battery change

## DIMENSIONS

| | |
|---|---|
| **Length** | 5.36" (13.6 cm) |

## MATERIALS

| | |
|---|---|
| **Body** | Anti-static Impact Modified PC/PBT |
| **O-Ring** | Buna-N |
| **Lens** | Anti-static PMMA |
| **Shroud** | Anti-static Impact Modified PC/PBT |
| **Clip** | Anti-static Impact Modified PC/PBT |

## COLOURS

High Visibility Yellow

## LIGHT SPECS

| | |
|---|---|
| **Lamp Type** | LED |
| **Lamp Secondary Type** | LED |

## POWER

| | |
|---|---|
| **Battery Size** | AA |
| **Battery Type** | NiMH |
| **Battery Quantity** | 4 |
| **Batteries Included** | yes |
| **Rechargeable** | yes |
| **Charge Time** | 5 hrs |
| **Battery Level Indicator** | 3 Blue LEDs |
| **Volts** | 4.8v |

## WEIGHT

| | |
|---|---|
| **Weight With Batteries** | 14.6 oz (414 gr) |

| | |
|---|---|
| **Weight Without Batteries** | 11.0 oz (312 gr) |

## SWITCH


| | |
|---|---|
| **Switch Type** | Push Button |
| **Light Modes** | High / Low / Flashing |

## CERTIFICATIONS

**ATEX Zone 0**

## OTHER

| | |
|---|---|
| **Minimum Pack** | 1 |
| **Package Code** | B |

| FL1 STANDARD | HIGH | LOW | DOWNCAST |
|---|---|---|---|
|  | 194 LUMENS | 92 LUMENS | 24 LUMENS |
|  | 3h 30mins | 6h 45mins | 20h 0mins |
|  | 256m | 161m | 24m |
|  | 16392cd | 6454cd | 146cd |
|  | IPX4 | | |

## ACCESSORIES



**3769**
Replacement Battery



**3770F**
Battery Charger Base



**6061F**
Direct Wiring Rig for Fast Charger



**8056F**
12v Plug-in for Fast Charger

**Peli**
c/ Provença, 388, Planta 7 • Barcelona, Spain 08025 • Phone: +34 934 674 999
info@peli.com • www.peli.com

*Document created on 10-26-26*